

Chameleon Wall Switch

The Chameleon Wall switch works via radio, and, just like a remote, programs straight into the receiver. Its' main advantages are:

- Compatibility with up to 24 of the main brands in the market.
- Easy installation – The Wall Switch requires no cables or holes in the wall, simply programme it in and place where you require.
- The rear of the Wall Switch is mostly covered, leaving only the switches exposed, making the Wall Switch as easy to programme as possible.



To use your Wall switch, simply set the switches to provide a coding compatible with you system (see table below)

Programming the Wall Switch into the receiver is done in the same way as programming a remote control.

The process to change the battery is as follows:

1. Remove the 2 small screws on either side holding the rear casing to the front.
2. Loosen the 2 screws at the top.
3. Remove the casing.
4. Change the battery and refit the casing carefully ensuring the two pins are correctly located and screw in place.

Battery size 23A 12V



Wall Switch mounted in optional ES400 External Housing

Below are the dipswitch positions for each brand:

ITEM		+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1		R/F code	Brand	Remarks
1	ON				X													SW =
	OFF	X	X	X			X	X	X	X	X	X	X	X		Rolling C	BFT	HIDDEN KEY
2	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X		X		X	X	X	X	X	X	X			Rolling C	NICE SMILO	
3	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X				X	X	X	X	X	X		X		Rolling C	BENINCA	
4	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X		X	X		X	X	X	X	X	X				Rolling C	DEA	
5	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				SW =
	OFF	X		X			X	X	X	X	X		X	X		Rolling C	ERREKA	HIDDEN KEY
6	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X			X		X	X	X	X	X		X			Rolling C	GiBiDi	
7	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X					X	X	X	X	X			X		Rolling C	Fox	
8	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF		X	X	X		X	X	X	X	X					Rolling C	Vario	
9	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF		X	X			X	X	X	X		X	X	X		Rolling C	FAAC 433	
10	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF		X		X		X	X	X	X		X	X			Rolling C	Mutant Code	
11	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF		X				X	X	X	X		X		X		Rolling C	FORESEE	
12	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF			X	X		X	X	X	X		X				Rolling C	Aprimatic	

ITEM		+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1		R/F code	Brand	Remarks
1	ON								X									
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Proteco	
2	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Ditec	
3	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Motorline	
4	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Prastel	
5	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Roltore	
6	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Rolling Code	Nice FloR	
7	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	King Gate	
8	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Came	
9	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Key	
10	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Roger	
11	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Telcoma Tango2	
12	ON	+8	+4	+2	+1		Sp	C/T	R/F	+16	+8	+4	+2	+1				
	OFF	X	X	X	X		X	X		X	X	X	X	X		Fixed Code	Marantec	